

Date 03.06.08	Ref. No. <b>06TV169R8</b>	Model <b>KDL-40W2000, KDL-46W2000</b>	BC
Subject <b>Software Packages Follow-up for WAX-2F Chassis [REVISION 8]</b>			IRIS

## SYMPTOM

The latest software packages are valid for all WAX-2F models and solve the problems mentioned in the Technical Bulletins listed below.

<i>Technical Bulletin</i>	<i>Subject</i>
06TV165R*	Dark "Mura" Phenomenon at Low Temperature
07TV018	Green Picture with Specific External Equipment
07TV019	Black Bars during VHS Playback
07TV036R*	Uneven Uniformity Problem
07TV053R*	Picture Blanking during VHS Playback
07TV054R*	RGB Picture Distortion with JVC DVD Player
07TV055R*	No Audio from SCART on Some Digital Radio Stations

Also included	Czechia Digital Broadcast Problem
	Finland DVB Subtitling Problem: random disappearance of subtitles
	The Netherlands WSS Problem: screen format change with specific broadcasting due to wrong WSS signal detection
	OSD Change
	Live Colour Improvement

## SOLUTION

1. Install the latest software package as explained in Technical Bulletin 06TV168, using the zip file indicated in the table on the next page and attached to this document. The package to be installed depends on whether the serial number of the set is included in **list A** or **list B** below, and the panel type of the set.

**Important:** Check Technical Bulletin **07TV087R\*** to identify old from new panel types.

<i>Model</i>	<i>Serial numbers</i>	
	<b>LIST A</b>	<b>LIST B</b>
KDL-40W2000	/	3000001~
	4000001~4030660	4030661~
	4300001~4342544	4342545~
KDL-46W2000	4000001~4006553	4006554~
	4300001~4312647	4312648~

Date	Panel	List	Software Package	Attachment	
June 2008	NEW	A	PKG1058	PKG1058_N_ADJ.ZIP	DM2.15.511
					TM1.500
					TD1.702
	B		PKG1057	PKG1057_N_ADJ.ZIP	DM2.15.600
					TM1.500
					TD1.702
	OLD	A	PKG1051	PKG1051_N_ADJ.ZIP	DM2.15.511
					TM1.024
					TD1.010
	B		PKG1050	PKG1050_N_ADJ.ZIP	DM2.15.600
					TM1.024
					TD1.010

2. Check whether the update has been performed correctly.

- Check the model name by entering  
[USER MENU] ⇒ [SETTINGS] ⇒ [SET-UP] ⇒ [PRODUCT INFORMATION].
- Check the software version in the service menu via remote control by entering  
[INFORMATION] ⇒ [5] ⇒ [VOLUME +] ⇒ [POWER] in standby mode.

The menu below will appear. Check whether menu names and file names correspond. For example:

MAIN VER.	1018	PKG1035E_N_ADJ
BOOT VER.	1005	TM1018_TH1201_TS1008_TD1009_40
H PACK VER.	1201	wax2_mheg
S PACK VER.	1008	TM1018_TH1201_TS1008_TD1009_46
CHECK SUM	901A	wax2_mheg
NVM VER.	1009	
EMMA VER.	2.5.511	
STARTER	0.0.30	
ETI	h min	