



US006727664B2

(12) **United States Patent**  
**Miller et al.**

(10) **Patent No.:** **US 6,727,664 B2**  
(45) **Date of Patent:** **\*Apr. 27, 2004**

(54) **PORTABLE FLUORESCENT DROP-LIGHT**

(75) Inventors: **Thomas J. Miller**, Chino Hills, CA  
(US); **Zhou Dong Yue**, Guangdong  
(CN)

(73) Assignee: **TMC Enterprises, a division of Tasco  
Industries, Inc.**, Diamond Bar, CA  
(US)

(\*) Notice: Subject to any disclaimer, the term of this  
patent is extended or adjusted under 35  
U.S.C. 154(b) by 0 days.

This patent is subject to a terminal dis-  
claimer.

4,791,338 A	12/1988	Dean et al. ....	315/209 R
4,928,038 A	5/1990	Nerone .....	315/209 R
5,049,783 A	9/1991	Kroening .....	315/102
5,068,577 A	11/1991	Brown .....	315/307
5,072,159 A	12/1991	Schlenk .....	315/278
5,088,015 A	* 2/1992	Baggio et al. ....	362/217
5,301,093 A	* 4/1994	Baggio .....	362/223
5,493,482 A	* 2/1996	Bowen .....	362/219
5,500,792 A	3/1996	Jeon et al. ....	315/291
5,519,289 A	* 5/1996	Katyl et al. ....	315/209 R
5,528,477 A	* 6/1996	Carmo .....	362/260
5,537,010 A	7/1996	Johnson et al. ....	315/289
5,635,799 A	* 6/1997	Hesterman .....	315/127
5,848,836 A	* 12/1998	Graber et al. ....	362/223
5,854,538 A	12/1998	Krummel .....	315/105
5,998,930 A	12/1999	Upadhyay et al. ....	315/106
6,031,339 A	2/2000	Andrews .....	315/224
6,169,373 B1	* 1/2001	Riesinger .....	315/178
6,534,926 B1	* 3/2003	Miller et al. ....	315/224

(21) Appl. No.: **10/316,219**

(22) Filed: **Dec. 10, 2002**

(65) **Prior Publication Data**

US 2003/0080697 A1 May 1, 2003

#### Related U.S. Application Data

(63) Continuation of application No. 09/644,765, filed on Aug.  
23, 2000, now Pat. No. 6,534,926.

(60) Provisional application No. 60/196,767, filed on Apr. 12,  
2000.

(51) **Int. Cl.<sup>7</sup>** ..... **H05B 37/02**

(52) **U.S. Cl.** ..... **315/224; 315/209 R; 362/260;**  
**362/223**

(58) **Field of Search** ..... **315/224, 209 R,**  
**315/225, 178, 180, 182, 313, 320, 323,**  
**33, 35, 38; 362/260, 223, 222, 225, 217**

(56) **References Cited**

#### U.S. PATENT DOCUMENTS

4,109,307 A	8/1978	Knoll .....	315/224
4,127,893 A	11/1978	Goepel .....	363/37
4,277,726 A	* 7/1981	Burke .....	315/307

\* cited by examiner

*Primary Examiner*—James Clinger


*Assistant Examiner*—Ephrem Alemu

(74) *Attorney, Agent, or Firm*—Knobbe, Martens, Olson &  
Bear, LLP

(57) **ABSTRACT**

A hand-held fluorescent lamp assembly powered by typical line supply of 120 VAC, 60 Hz via an attached power cord and employing multiple commonly available fluorescent lamps. The assembly includes switches to independently control the multiple fluorescent lamps. The assembly includes lightweight solid state power regulation components. The power regulation circuit employs a self-oscillating circuit that is approximately matched in frequency of oscillation to the natural frequency of the fluorescent lamp load to automatically ignite the fluorescent lamps. The power regulation circuit includes circuit elements to automatically protect the ballast circuit and lamps from overdrawing in the run state and from abnormal load conditions.

**7 Claims, 5 Drawing Sheets**






FIG. 1A




FIG. 1B




FIG. 2




FIG. 3




FIG. 4




FIG. 5

**PORTABLE FLUORESCENT DROP-LIGHT****RELATED APPLICATIONS**

This application is a continuation of application Ser. No. 09/644,765, filed Aug. 23, 2000 now U.S. Pat. No. 6,534, 926 which claims the benefit of U.S. Provisional Application No. 60/196,767 entitled Portable Fluorescent Drop-Light filed Apr. 12, 2000.

**BACKGROUND OF THE INVENTION****1. Field of the Invention**

The present invention relates to the field of electrical devices and in particular to a portable fluorescent drop-light including multiple lamps connected in parallel with switches to allow the individual lamps to be independently turned on or off and a ballast circuit comprising solid-state devices to drive and protect the multiple lamps with or without integral starters.

**2. Description of the Related Art**

Circumstances often arise around the home and in shops in which a person wishes to illuminate an area that is not adequately illuminated by the installed light fixtures. Flash-lights are sometimes used in these circumstances, however as they are powered by batteries, they typically do not offer the illuminating power of hardwired lights. In addition the batteries are of limited lifespan and the light from a flash-light is typically focussed whereas the desire is often for more diffused illumination.

Drop-lights are powered by line supply (120 VAC, 60 Hz) but are portable, hand-held assemblies to thereby allow the user to provide light where the installed light fixtures do not provide coverage. Drop-lights are powered from wall receptacles via a power cord and are not subject to the power and life span limitations of batteries. Drop-lights are typically provided with a hook to allow them to be hung in position and typically employ an incandescent light bulb to provide the illumination.

Incandescent light bulbs consist of a glass bulb enclosing a tungsten filament in an inert gas or highly evacuated atmosphere. When an electric current passes through the filament, the filament heats up to a high temperature at which point it becomes incandescent and provides illumination. The atmosphere surrounding the filament is either an inert gas or evacuated to near vacuum in order to minimize deleterious reactions of the tungsten filament at elevated operating temperatures. Tungsten is used because it has an extremely high melting point and can maintain the high temperatures necessary for incandescence with minimal deterioration.

Incandescent light bulbs are a well-developed technology and are economical to purchase. However, incandescent light bulbs are not particularly economical to operate. Incandescent light bulbs are not very efficient at converting electrical energy to light energy. A typical incandescent lamp produces approximately 20 lumens per watt of electrical power consumed. Much of the electrical energy is converted to heat. The tungsten filament in a typical incandescent bulb operates at approximately 1500–2700K. A 75–100W incandescent bulb will get too hot to touch during operation.

The high operating temperatures of incandescent light bulbs present some particular drawbacks when used in drop-lights. The heat emitted by the bulb itself makes them uncomfortable to have in close proximity to a person for an extended period. Also, the high operating temperature and fine structure of the tungsten filaments makes them suscep-

tible to breaking if they are jarred in use. Since a drop-light is portable, users will generally move them about during use to place them in the optimal position for illuminating their work. This movement while the filament is hot stresses the filament and an incandescent light bulb in a drop-light will generally have a much shorter life span than it would in a stationary light fixture. Finally, the bulb enclosure is typically a thin glass bulb susceptible to breakage and, if the bulb breaks, the hot tungsten filament is exposed. It can be easily appreciated that this could present an extreme fire hazard if the user is working around flammable materials with relatively low flash points.

Gas discharge lamps are an alternative means of converting electrical energy to light energy that offer significant advantages to incandescent lighting, particularly in drop-light applications. Gas discharge or fluorescent lamps, consist of a gas or vapor filled tube that is provided with electrodes at either end of the tube. When a high enough voltage is applied between the electrodes, the gas inside the tube partially ionizes and undergoes a phase change to the plasma state. The plasma state gas is conductive and serves as a conductor for an electric arc between the electrodes. As current passes between the electrodes, electrons collide with gas molecules within the tube. When an electron collides with a gas atom, an electron in the atom's shell is boosted to a higher energy level. This higher energy level is not a stable condition and when the electron falls back to its normal energy level, a photon of light is emitted. Thus the gas luminesces and gives off the characteristic "fluorescent" light.

Fluorescent lights convert more of the supplied electrical energy to light energy than incandescent lights do and fluorescent lights operate at lower external temperatures. The light emitting medium in fluorescent lights is a gas that cannot "break" like the thin tungsten filament in an incandescent light bulb. While a broken fluorescent light tube does present some health hazards, there is not the tungsten filament operating at 1500–2700K to present an ignition source for flammable materials.

Typically, a higher voltage is required to initiate the plasma state than is required to maintain the plasma state and the luminescence. Also, once the gas starts becoming a plasma, the effective resistance between the electrodes becomes negative. More of the gas will become plasma and the fluorescent light tube will tend to draw more and more current even though the applied voltage stays the same. If this phenomenon is allowed to continue unabated, the tube will overdraw and burn itself out. The excessive current draw can also damage the supply circuit.

Typical practice in the art is to provide a damping circuit that can function both to "spark" the gas tube into operation and also to limit the current that is supplied to the tube. This damping has typically been accomplished with a ballast that primarily consists of a large transformer/inductor. The ballast functions both to transform the supplied line voltage (which is an AC voltage) to a high enough potential to ensure that the fluorescent tube "lights off" and also to provide a high enough inductance in the supply circuit to prevent the fluorescent light tube from overdrawing and damaging itself or the supply circuit during operation.

Alternatively, fluorescent bulbs are available that include integral "starting" ability. The ballast circuits for such lamps provide an appropriate voltage to the lamps and the lamps start themselves. The ballast circuit then regulates the current draw in a similar manner to that previously described for non-self starting bulbs.

The requirements of a ballast for typical line supplies (120 VAC, 60 Hz) are such that the wire gauge and number of turns in the coils and size of the magnetic coupling core result in ballast's that are relatively bulky and heavy. To overcome the size and weight issue, previous art has been developed that incorporates solid state devices into circuit designs to allow similar ballasting functions to be performed in much more compact and lighter assemblies. This has enabled lightweight hand-held fluorescent drop-lights to be brought to market.

The typical design for hand-held fluorescent drop-lights powered by line supplies uses either a twin tube standard bulb or a quad tube standard bulb. The twin tubes have the advantage that they are less expensive and more readily available. However, the twin tubes are of approximately half the power (13W) and light output of the quad tube lamps. The quad tube design offers approximately twice the power (27W) and illumination of a single twin tube, however the quad tube bulb is more expensive to produce and purchase and is not as readily available. The size and weight restrictions of drop-light applications generally preclude employing multiple independent lamp circuits as the additional ballast circuits required for each lamp occupy too much space and are too heavy to make such a drop-light handy in use.

From the foregoing, it can be seen that there is a continuing need for a portable hand-held lamp that is efficient to operate and does not operate at excessively high temperatures. The lamp should be sturdy and durable and replacement bulbs should be inexpensive and readily available. It would be a further desirable feature to provide variable illumination and as light-weight and compact a lamp as possible.

SUMMARY OF THE INVENTION

The aforementioned needs are satisfied by the present invention, which in one embodiment, is a portable fluorescent drop-light that employs a single self-oscillation circuit to power two fluorescent light bulbs in parallel. The invention further comprises a single protection circuit for both bulbs. By placing the two bulbs in parallel, the drop-light will function with either bulb alone or with both together, yet maintains the weight and size advantages of using a single set of circuit components to ballast both bulbs. The drop-light incorporates solid state devices in the ballast circuit to reduce the weight of the portable fluorescent drop-light compared to similar lights using traditional ballasts. The advantage of having two bulbs is that this design provides additional light while still using commonly available and inexpensive twin-tube standard bulbs. In addition, the drop-light is provided with switches so that the user can turn on only one of the bulbs when not as much light is needed thereby conserving energy. These and other objects and advantages of the present invention will become more fully apparent from the following description taken in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1A shows a top view of an assembled portable fluorescent drop-light;

FIG. 1B shows a side view of an assembled portable fluorescent drop-light;

FIG. 2 is a perspective view of the assembled electrical components of the portable fluorescent drop-light;

FIG. 3 is a circuit diagram of a ballast circuit for the portable fluorescent drop-light suitable for non-self-starting lamps;

FIG. 4 is a circuit diagram of an alternative embodiment of a ballast circuit for the portable fluorescent drop-light suitable for self-starting lamps; and

FIG. 5 is a section view of the starter elements of a self-starting fluorescent lamp.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

Reference will now be made to the drawings wherein like numerals refer to like parts throughout. A portable fluorescent drop-light **100** is shown in a top view in FIG. 1A and in a side view in FIG. 1B. The portable fluorescent drop-light **100** provides hand-held portable illumination around a home, office, or shop. The portable fluorescent drop-light **100** draws electrical power from a typical wall receptacle and converts the electrical energy to light energy in a manner that will be described in greater detail below. The portable fluorescent drop-light **100** is approximately 1 kg in mass and 30 cm in length.

The portable fluorescent drop-light **100** comprises a hook **102**. The hook **102** is preferably made of a light-weight strong plastic material of a type well known in the art. The hook **102** is fixedly attached to a first end **103** of a right enclosure shell **104** and a left enclosure shell **106** so as to be rotatably moved about an axis. The hook **102** allows the portable fluorescent drop-light **100** to be hung from other objects thereby allowing a user to free their hands for other tasks.

The right **104** and left **106** enclosure shells are preferably made of a light-weight strong plastic material of a type well known in the art. The right **104** and left **106** enclosure shells are substantially mirror images of each other. The right **104** and left **106** enclosure shells are provided with a plurality of support structures extending outwards from their inner surface to allow the right **104** and left **106** enclosure shells to secure and locate other component parts of the portable fluorescent drop-light **100** in a manner that will be described in greater detail below. The outsides of the right **104** and left **106** enclosure shells also provide a gripping surface **105** adjacent a second end **107** for a user of the portable fluorescent drop-light **100**. The gripping surface **105** of this embodiment is generally cylindrical and is approximately 10 cm×5 cm×4 cm. The gripping surface **105** of the right **104** and left **106** enclosure shells encloses a ballast circuit assembly **140** in a manner that will be described in greater detail below.

The portable fluorescent drop-light **100** also defines a lamp cavity **111**, which is covered by a lens **112**. The lamp cavity **111** is adjacent the first end **103** and is adapted to receive a plurality of fluorescent lamps **130**, **150** in the manner shown. The lens **112** is transparent plastic that is configured to closely mate with the right **104** and left **106** enclosure shells in a manner that will be described in greater detail below. The lens **112** covers and protects fluorescent lamps **130**, **150** from impact, dirt, and other contamination. The fluorescent lamps **130** of this embodiment are twin tube, 13W PL lamps of type FL-26 available from numerous suppliers, such as Phillips, and provide illumination when supplied with regulated electrical power in a well known manner.

The portable fluorescent drop-light **100** of this embodiment also comprises a switch **114** that is held in place between the right **104** and left **106** enclosure shells so as to be interposed between the gripping surface **105** and the cavity **111** in the manner shown. The switch **114** is a two pole electrical switch rated for at least 12A at 125 VAC of



a type well known in the art. The switch **114** selectively provides regulated electrical power from a ballast circuit **132**, **152** to the fluorescent lamps **130**, **150** in a manner that will be described in greater detail below.

The portable fluorescent drop-light **100** also comprises an electrical outlet **116** that is held in place between the second end **107** of the right **104** and left **106** enclosure shells and that is adapted to receive a standard 3 prong grounded plug. The electrical outlet **116** is rated for 15A at 125 VAC and in this embodiment is a type RF-6001 available from Rongfeng of China. The electrical outlet **116** makes the electrical power supplied to the portable fluorescent drop-light **100** available to other devices that can be connected to the electrical outlet **116** in a manner well known in the art.

The portable fluorescent drop-light **100** also comprises a strain relief **120**, a power cord **122**, and a plug **124**. The strain relief **120** is fixedly attached to the second end **107** of the right **104** and left **106** enclosure shells in a manner that will be described in greater detail below and also fixedly attached to a first end **121** of the power cord **122** in a well known manner. The strain relief **120** alleviates tensile and lateral forces that arise between the power cord **122** and the right **104** and left **106** enclosure shells due to movement of the portable fluorescent drop-light **100** during use. The power cord **122** is a three twisted conductor 16 AWG power cable of a type well known in the art. The plug **124** is a grounded three prong male connector of a type well known in the art. The plug **124** is physically and electrically connected to a second end **123** of the power cord **122** in a well known manner. The first end **121** of the power cord **122** is physically and electrically connected to the electrical outlet **116** and to the ballast circuit **132**. Thus, electrical power supplied to the plug **124** is also supplied to the electrical outlet **116** and to the ballast circuit **132**, **152** via the power cord **122**.

A first end **131** of the fluorescent lamps **130**, **150** is connected to a bulb socket **126**. The bulb socket **126** is adapted to physically and electrically connect to the first end **131** of the fluorescent lamps **130**, **150** in a well known manner. The bulb socket **126** also physically locates the fluorescent lamps **130**, **150** within the lamp cavity **111** and supplies them with regulated electrical power in a manner that will be described in greater detail below.

The portable fluorescent drop-light **100** also comprises a ballast circuit assembly **140** located with the right **104** and left **106** enclosure shells adjacent the gripping surface **105** as shown in FIG. 1B in dashed lines. The ballast circuit assembly **140** comprises a circuit board **146** and the ballast circuit **132**, **152** mounted thereon as shown in FIG. 2. The circuit board **146** is approximately a 1" by 1.5" by 2.7" piece of non-conducting rigid material and serves as a mounting surface for the various components of the ballast circuit **132**. The proper material of the circuit board **146** and manner of mounting electrical components thereon are both well known to those skilled in the art. The ballast circuit **132**, **152** receives electrical power from the power cord **122** and provides regulated electrical power to the fluorescent lamps **130**, **150** in a manner that will be described in greater detail below.

The ballast circuit assembly **140**, bulb socket **126**, fluorescent lamps **130**, **150**, power cord **122**, strain relief **120**, electrical outlet **116**, switch **114**, lens **112**, and hook **102** are all placed adjacent the inner surfaces of the right **104** and left **106** enclosure shells such that each of the listed items is adjacent a corresponding support structure such as have been previously described. The right enclosure shell **104** is

positioned so as to be adjacent and respectively aligned with the left enclosure shell **106**. Screws **110** are then positioned in attachment holes **108** provided in the right **104** and left **106** enclosure shells and tightened in a well known manner so as to secure the right enclosure shell **104** to the left enclosure shell **106** and thereby locate and secure the other components of the portable fluorescent drop-light **100** within the right **104** and left **106** enclosure shells in the locations previously described.

FIG. 2 shows a perspective view of the electrical components of the portable fluorescent drop-light **100**. In the preferred embodiment, these components would be assembled together before being placed within the right **104** and left **106** enclosure shells as previously described. As shown in FIG. 2, a first end **121** of the power cord **122** is connected to the plug **124** and a second end **123** of the power cord **122** is connected to the strain relief **120**. A ground wire **142** of the power cord **122** is connected to the ground terminal of the electrical outlet **116** in a well known manner. The ground wire **142** grounds the portable fluorescent drop-light **100** in a manner well known in the art.

The conducting wires of the power cord **122** are connected to the ballast circuit assembly **140** via 18 AWG wire **134** and closed end connectors **136** in a manner well known in the art. The conducting wires of the power cord **122** are further connected to the corresponding terminals of the electrical outlet **116** via 14 AWG wire **144** and closed end connectors **136** in a well known manner. Thus, when the plug **124** is supplied with electrical power, the ballast circuit **132**, **152** and electrical outlet **116** are also supplied with electrical power via the power cord **122** and the 18 AWG **134** and 14 AWG **144** wire.

The ballast circuit **132**, **152** regulates the electrical power received via the 18 AWG wire **134** in a manner that will be described in greater detail below. In this embodiment, the ballast circuit **132**, **152** selectively provides this regulated power to the bulb socket **126** and thus to the fluorescent lamps **130**, **150** via 18 AWG wire **134** and the switch **114**. Regulated power may be selectively provided to the bulb socket **126** and the fluorescent lamps **130**, **150** by user actuation of the switch **114**. The switch **114** is a two-pole switch and is connected such that a user can select to supply regulated power to each fluorescent lamp **130**, **150** independently.

One embodiment of the ballast circuit **132** is shown in FIG. 3, wherein the ballast circuit **132** receives line supply, normally 120 VAC, 60 Hz. The embodiment of the ballast circuit **132** shown in FIG. 3 and described as follows is adapted for use with fluorescent lamps **130** without integral starter elements. Diodes **200** and **202** and capacitors **204** and **206** full-wave rectify, filter, and direct the input current through resistors **210** and **212** to charge capacitor **214**. When sufficient charge accumulates on the capacitor **214** to exceed the breakdown voltage of bi-directional diode **216**, the bi-directional diode **216** breaks down and passes current to the base of transistor **220** thereby forward biasing the emitter-base junction of the transistor **220** and also passes current through resistor **230** and inductor **226**. Transistor **274** forms part of a protection circuit and is normally cut-off as will be described in greater detail below. Diode **222** is connected between the emitter and base of transistor **220** to limit the reverse biasing of the emitter-base junction and thus the emitter-base junction depletion capacitance thus allowing transistor **220** to turn on more rapidly.

The collector voltage of transistor **220** is held at or above the base voltage of transistor **220** by forward-biased diode

282, thus the collector-base junction of transistor 220 is reverse biased and the transistor 220 is in the active mode of operation. The collector of the transistor 220 in the active mode rapidly draws off accumulated charge from the capacitor 214 via the forward biased diode 282 and passes it through resistor 224. When sufficient charge has been removed from the capacitor 214, the voltage across the capacitor 214 falls below the breakdown voltage of the bi-directional diode 216 and the bi-directional diode 216 recovers its blocking state and ceases passing current. The cessation of current to the base of transistor 220 cuts off the transistor 220, thereby allowing charge to accumulate again on capacitor 214. It can be appreciated that the capacitor 214 and the transistor 220 operate in opposition via the bi-directional diode 216.

A circuit loop 292 is formed by capacitor 204, capacitor 290, the closed switch 114, a fluorescent lamp 130, inductor 246, inductor 232, the collector and emitter legs of transistor 220, resistor 224, and diode 202 with the line supply. In a similar manner, a substantially parallel circuit loop 294 is formed by a fluorescent lamp 130 and inductor 250. It should be noted that the two circuit loops 292, 294 with the fluorescent lamps 130 share common circuit elements except the parallel branches of the fluorescent lamps 130 and their associated inductors 246 or 250.

As the line supply drives current through the circuit loops 292 and 294, inductor 232 saturates, the voltage across inductor 226 falls, which pulls down the base voltage of transistor 220 until the point at which transistor 220 enters cut-off. Transistor 220 cutting off directs the current in inductor 232 through inductor 242, which further passes through resistor 244 to the base of transistor 234. This base current forward biases the emitter-base junction of transistor 234 and the transistor 234 enters the active mode of operation and passes emitter current through resistor 240. Diode 236 is connected between the emitter and base of transistor 234 to limit the reverse biasing of the emitter-base junction and thus the emitter-base junction depletion capacitance thus allowing transistor 234 to turn on more rapidly. Resistor 284 connects the collector of transistor 234 to diode 282. The additional collector current of transistor 234 in the active mode accumulates additional charge on capacitor 290 and the voltage on capacitor 290 increases above the line supply voltage.

As transistor 234 is becoming active, capacitor 286 discharges and the current flows through capacitor 286, capacitor 290, the fluorescent lamps 130, inductors 246 and/or 250, and inductor 232. As capacitor 286 discharges, capacitor 214 charges until the point where sufficient charge accumulates on capacitor 214 to return the transistor 220 to the active mode of operation as previously described and to cut off transistor 234. This alternation between active mode operation and cut-off of the transistors 220 and 234 provides a self-oscillation circuit, which is adjusted by component selection to have a natural frequency that, in this embodiment, is approximately 37 kHz.

The series connection of the capacitor 290, the inductors 246 and/or 250, the reactance of the fluorescent lamps 130 (primarily capacitive), and inductor 232 also form an oscillating circuit element with a natural frequency that, in this embodiment, is approximately 37 kHz. The close match in oscillation frequencies between the load branch and the self-oscillation circuits of transistors 220 and 234 provides charging of capacitor 290 to voltages much higher than those provided by the line supply. This high voltage on capacitor 290 initiates a plasma state within the fluorescent lamps 130 and places them in a run condition automatically, without

requiring any special user action. The reactance of the fluorescent lamps 130 decreases when they enter the run condition and accordingly a limiting/protection circuit is provided.

Inductor 252 which is coupled to the inductor 246 and/or inductor 254 which is coupled to the inductor 250 generate voltages which drives current through diode 262 and resistor 264 and/or diode 256 and resistor 260. This induced current charges capacitor 266. A resistor 270 is connected in parallel to the capacitor 266 as a bypass. When the accumulated charge on the capacitor 266 exceeds the breakdown voltage of bi-directional diode 272, the bi-directional diode 272 breaks down and passes current to the base of transistor 274, thereby forward biasing the emitter-base junction. Transistor 274 becomes active and bleeds off current from the base of transistor 220, which cuts off transistor 220 and terminates the self-oscillation previously described.

The current passing through bi-directional diode 272 also forward biases diode 276 and injects current into the gate of thyristor 280. This injected gate current places the thyristor 280 into an on state and allows the thyristor 280 to pass forward current and drain off the charge accumulated on capacitor 214 which removes the potential to inject current into the base of transistor 220 which also inhibits the self-oscillation previously described. It can be appreciated that the charging of capacitor 266 to the breakdown voltage of the bi-directional diode 272 before activating the protection circuitry permits a limited degree of imbalance between the loads or other abnormal load conditions without disabling the ballast circuit 132. In this embodiment, the protection circuit is activated for a portion of each oscillation cycle so as to allow the ballast circuit 132 to provide both the high voltage required to place the fluorescent lamps 130 into a run condition in the manner previously described, yet also inhibit the fluorescent lamps 130 from overdrawing and damaging themselves or the ballast circuit 132 as they enter the run condition.

It can be appreciated by one skilled in the art that the singular circuit elements of the ballast circuit 132 herein described supplying multiple fluorescent lamps 130 reduces the number of circuit elements necessary for the ballast circuit 132 of this embodiment. By reducing the number of circuit elements needed, the ballast circuit assembly 140 comprising the ballast circuit 132 is advantageously reduced in size so as to readily fit within the right 104 and left 106 enclosure shells in the manner previously described. Thus, the portable fluorescent drop-light 100 of this embodiment can be readily held in the hand and easily positioned by one of normal size and ability.

FIG. 4 shows an alternative embodiment of a ballast circuit 152. The ballast circuit 152 as shown in FIG. 4 and described as follows provides regulated electrical power to fluorescent lamps 150 that include an integral starter element. The ballast circuit 152 receives line supply, normally 120 VAC, 60 Hz. Fuse 300 and diodes 302 and 304 and capacitors 306 and 310 full-wave rectify, filter, and direct the input current through resistors 312 and 314 to charge capacitor 316. When sufficient charge accumulates on the capacitor 316 to exceed the breakdown voltage of bi-directional diode 320, the bi-directional diode 320 breaks down and passes current to the base of transistor 322 thereby forward biasing the emitter-base junction of the transistor 322. Current also passes through resistor 324 and inductor 326. Diode 356 is connected between the base and emitter of transistor 322 in order to limit the reverse bias on the base-emitter junction of transistor 322 to thereby allow the transistor to turn on more rapidly. The collector of transistor 322 is held at a higher

voltage than the base by forward biased diode **330** and thus transistor **322** is in the active mode of operation. While transistor **322** is in the active mode of operation, a transistor **352** is cut-off.

When the transistor **322** goes active, current starts to flow with a high initial di/dt in the circuit branch comprising capacitors **306** and **332**, fluorescent lamp **150**, inductors **334** and **336**, transistors **322**, resistor **340**, diode **304**, and fuse **300**. The current flow causes capacitor **322**, fluorescent lamp **150**, and inductors **334** and **336** to saturate which causes the di/dt to decrease. As di/dt decreases, the voltage across inductors **334** and **336** decreases which decreases the voltage at the collector of transistor **322** and transistor **322** enters saturation, while the voltage across capacitor **332** reaches higher voltages than line supply. The current flowing in the circuit branch then reverses through resistor **342** and capacitor **344** as well as through inductor **346** and resistor **350** to trigger the base of transistor **352**. Transistor **352** enters the active mode of operation. A diode **360** is connected between the base and emitter of transistor **352** to limit the reverse bias on the base-emitter junction of transistor **352** and thereby allow transistor **352** to turn on more rapidly. Transistor **352** entering the active mode of operation is accompanied by transistor **322** becoming cut-off as the current flow reverses as previously described.

The circuit branches containing transistors **322** and **352** alternate between operation in the cut-off and active modes. The alternation between transistors **322** and **352** has a natural frequency which is approximately equal to the natural frequency of the series connection of the capacitor **332**, the fluorescent lamp **150** and inductors **334** and **336** wherein the frequencies of these oscillations are approximately equal and in this embodiment approximately 35 kHz. The oscillating current flow induces high voltage to appear on capacitor **332**. Since capacitor **332** is connected to the fluorescent lamp **150**, the high voltage produced provides the ignition voltage necessary to activate starter elements **154** in the fluorescent lamps **150** in a manner that will be described in greater detail below with reference to FIG. 5. Thus, the ballast circuit **152** of this embodiment also automatically starts the fluorescent lamps **150** without any special user action.

The ballast circuit **152** also comprises a parallel, substantially identical circuit comprising resistors **362** and **364**, capacitor **366**, bi-directional diode **370**, transistor **372**, resistor **374**, inductor **376**, diode **380**, capacitor **382**, inductors **384** and **386**, resistors **390** and **392**, capacitor **394**, inductor **396**, resistor **400**, transistor **402**, resistor **404**, and diodes **406**, **410**. The placement, characteristics, and operation of these components are substantially identical to those for the corresponding components in the parallel circuit as previously described and will not be repeated here. It should be appreciated that the parallel circuits herein described are also selectively activated by user actuation of the switch **114** in the manner previously described for the embodiment of the ballast circuit **132** described with reference to FIG. 3.

The ballast circuit **152** of this embodiment suitable for self-starter lamps **150**, while employing more circuit elements (45 total) than the ballast circuit **132** of the embodiment previously described suitable for non-self-starter lamps **130** (38 total), retains a desirably low overall size and weight, which in this embodiment is approximately 1" by 1.5" by 2.7", by dispensing with some of the bulkier and more massive circuit elements of the ballast circuit **132** of the embodiment suitable for use with non-self-starter lamps **130**. In particular, the ballast circuit **152** of this embodiment dispenses with inductors **232**, **250** and **254**, and **252** and **246**

of the ballast circuit **132** of the previous embodiment. Inductors **250** and **254** share a common core as do inductors **252** and **246** and are relatively bulky and massive components as will be appreciated by those skilled in the art. Inductors **334** and **336** and **384** and **386** perform similar circuit functions to the bulkier and more massive inductors **232**, **250** and **254**, and **252** and **246**. Thus, the ballast circuit **152** of this embodiment is able to have essentially the same functionality of the ballast circuit **132** of the previous embodiment as previously described with more circuit elements while retaining substantially the same overall size and weight.

The fluorescent lamps **150** with integral starters comprise starter elements **154** as shown in FIG. 5. The starter elements **154** of this embodiment comprise a plurality of flexible bi-metallic elongate strips that are placed in proximity so as to form capacitors in a well known manner. When the ballast circuit **152** first begins to supply the regulated electrical power to the fluorescent lamps **150** in the manner previously described, such as initially turning on the portable fluorescent drop-light **100**, the fluorescent lamps **150** are not in a run condition. However, the regulated electrical power provided to the fluorescent lamps **150** is thereby provided to the starter elements **154**. The current alternately flowing through the starter elements **154** will create alternating electric fields between adjacent starter element **154** strips as the current flows through the material of the starter elements **154**. The starter elements **154** are constructed of conductive material such that the current passing through the starter elements **154** will result in bulk resistive heating of the starter elements **154**. The starter elements **154** are further constructed such that the resistive heating of the starter elements **154** causes adjacent starter elements **154** to deflect closer together such that the air gap between adjacent starter elements is reduced. As the air gap between adjacent starter elements is reduced, the regulated current supplied by the ballast circuit **152** will arc across the air gap. As current arcs across the starter elements **154** while regulated power is being supplied to the fluorescent lamps **150** in the manner previously described, the fluorescent lamps **150** will enter a run condition in a well known manner.

As the fluorescent lamps **150** enter a run condition, the electrical impedance of the fluorescent lamps **150** decreases in a known manner. The reduced impedance of the fluorescent lamps **150** results in substantially less current passing through the starter elements **154** and the starter elements **154** will thus cool and move further apart and cease arcing. Thus the starter elements **154** initiate the fluorescent lamps **150** into a run condition automatically when supplied regulated current by the ballast circuit **152** and then automatically return to a substantially inactive state once the fluorescent lamps **154** enter a run condition. The starter elements **154** allow the ballast circuit **152** to provide a lower starting voltage to the fluorescent lamps **150** than the ballast circuit **132** of the embodiment suited for use with fluorescent lamps **130** without integral starters while still facilitating the fluorescent lamps **150** rapidly and automatically entering a run condition. Thus the fluorescent lamps **150** of this embodiment are partially self-regulating and the ballast circuit **152** of this embodiment can dispense with the protection circuit of the ballast circuit **132** of the embodiment suited for use with fluorescent lamps **130** without integral starters. It should be appreciated that the starter elements **154** described herein are simply illustrative of one embodiment and similar function could be provided by alternative devices by one skilled in the art without detracting from the spirit of the present invention.

By employing solid-state devices in the ballast circuit **132** and employing single circuit elements to power multiple fluorescent lamps **130**, the portable fluorescent drop-light **100** offers greater economy of manufacture and purchase, smaller size, and lighter weight. By providing a self-oscillation circuit, which is matched in natural frequency that of the load, the ballast circuit **132** employs electrical resonance to create high voltages above line supply within the ballast circuit **132** which automatically starts the fluorescent lamps **130** without any additional user input thus providing additional convenience of use. The portable fluorescent drop-light **100** includes protection circuitry to automatically protect the portable fluorescent drop-light **100** from overdrawing and abnormal load conditions, thereby inhibiting damage to the assembly. The ballast circuit **152** adapted for use with fluorescent lamps **150** with integral starter elements **154** also automatically starts the fluorescent lamps **150** and eliminates bulky components with smaller components and thus maintains the advantageous reduced weight and size of the ballast circuit **132** adapted for use with fluorescent lamps **130** without integral starters.

By providing a switch **114** connected to independently connect the multiple fluorescent lamps **130** to the ballast circuit **132**, **152**, the portable fluorescent drop-light **100** allows the user to selectively activate single fluorescent lamps **130**, **150** separately or together to obtain optimal lighting and economy of energy usage. The portable fluorescent drop-light **100** employs commonly available and inexpensive twin tube 13W fluorescent lamps **130**, thereby providing better economy of purchase and less expensive and more convenient replacement of the fluorescent lamps **130** in case they wear out or break.

Although the preferred embodiments of the present invention have shown, described and pointed out the fundamental novel features of the invention as applied to those embodiments, it will be understood that various omissions, substitutions and changes in the form of the detail of the device illustrated may be made by those skilled in the art without departing from the spirit of the present invention. Consequently, the scope of the invention should not be limited to the foregoing description but is to be defined by the appended claims.

What is claimed is:

1. A hand-held fluorescent lamp assembly comprising:  
multiple twin tube PL fluorescent lamps;  
multiple switches coupled to the multiple twin tube PL fluorescent lamps respectively, wherein the multiple

- switches control the multiple PL fluorescent lamps independently;
- a ballast circuit configured to generate regulated power, wherein the regulated power is selectively provided to the multiple PL fluorescent lamps by the multiple switches wherein the ballast circuit is a single solid state ballast circuit adapted to provide regulated power to start and operate the multiple twin tube PL fluorescent lamps including multiple twin tube PL lamps with integral starters;
  - a housing having a first and a second shell that attach together so as to define a gripping surface sized so as to permit the user to hold the lamp assembly and the lamp cavity and wherein the two shells further define a space interior to the gripping surface which is sized to securely receive and retain the ballast circuit and wherein the lamp cavity receives the plurality of multiple twin tube PL fluorescent lamps and wherein the multiple switches are interposed between the gripping surface and the lamp cavity such that the user can activate the switches while holding the gripping surface.
  2. The hand-held fluorescent lamp assembly of claim 1, wherein the fluorescent lamps are twin tube bulbs.
  3. The hand-held fluorescent lamp assembly of claim 1, wherein the ballast circuit comprises:  
a full wave rectifier;  
a bi-directional diode; and  
a pair of transistors that alternately conduct to generate the regulated power.
  4. The hand-held fluorescent lamp assembly of claim 1, further comprising a hook configured to hang the hand-held fluorescent lamp assembly from other objects.
  5. The hand-held fluorescent lamp assembly of claim 1, wherein the multiple switches are two-pole electrical switches.
  6. The hand-held fluorescent lamp assembly of claim 1, further comprising a housing with a handle, wherein the handle encloses a circuit board for mounting and interconnecting components in the ballast circuit.
  7. The hand-held fluorescent lamp assembly of claim 6, wherein the multiple switches are interposed between the circuit board and the multiple fluorescent lamps.

\* \* \* \* \*