



**D BOARD TRANSISTOR VOLTAGE TABLE**

Transistor Voltage Table				
Ref No	(B) Base	(C) Collector	(E) Emitter	
Q276	0.7	4.0	-	-
Q277	10.0	-	9.7	-
Q278	-1.3	-	-	-
Q279	-1.3	-	-1.3	-
Q280	0.4	0.7	-	-
Q281	0.7	-	-	-
Q282	0.7	-	-	-
Q801	-1.0	101.0	-	-
Q802	-	136.0	-	-
Q803	9.0	15.0	-	-
Q804	11.3	0.1	-1.3	-
Q806	0.5	4.8	0.3	-
Q807	4.8	1.6	4.8	-
Q813	13.5	-	-	-
Q814	10.0	9.0	10.0	-
Q816	0.7	-	-	-
Q817	0.7	3.5	-	-
Q818	3.5	-	-	-
Q820	-	10.0	-	-
Q824	-	10.0	-	-
Q2701	-	2.3	-	-
Q1610	-0.5	2.2	-	-
Q1611	0.2	43.4	-	-

**D BOARD MARK**

Ref	KV-28WF3	KV-32WF3	Ref	KV-28WF3	KV-32WF3
C672	-	47MF	R842	33	-
C813	0.68MF	0.82MF	R852	390K	JW 5.0MM
C819	0.022MF	0.033MF	R853	220K	180K
C823	0.01MF	0.1MF	R871	100K	-
C842	0.0047MF	-	R872	470K	-
C848	-	150PF	R875	3.3K	JW 5.0MM
C849	-	150PF	R881	4.7	22
C863	-	0.1MF	R891	-	47K
C871	0.0082MF	-	R892	-	JW 5.0MM
C872	0.1MF	-	R910	-	-
C873	-	330PF	R1598	47K	6.8K
C874	1000PF	0.0047MF	R1599	-	6.8K
C878	0.1MF	-	R1600	-	6.8K
C879	-	100PF	R1639	-	220
C891	-	0.002MF	R1640	-	1.5K
C1616	-	0.0018MF	R1645	68K	4.7K
C819	0.1MF	0.018MF	R1646	2.2K	680
C1620	JW 5.0MM	220PF	R1647	JW 5.0MM	560
C1621	0.01MF	0.0047MF	R1648	10K	JW 5.0MM
C1629	0.0068MF	-	R1649	10K	-
C1633	-	10MF	R1650	10K	-
C1818	-	0.0022MF	R1651	33	-
CN746	-	4P	R1652	2.2K	-
D871	1S119-25TD	-	T803	1-246-897-11	1-247-776-11
IC508	-	LM2940T-8.0	T804	1-429-288-11	1-429-287-11
L813	0UH	-	T805	NX-4003	NX-4123
L1604	0UH	-	T806	DFT	-
PS1601	JW 5.0MM	LINK IC	T807	-	DFT
Q1603	-	2SC3840(3)	JW83	-	JW 5.0MM
Q1611	2SC4793	IRF620	JW84	-	JW 5.0MM
R010	-	47K	JW180	-	JW 5.0MM
R821	6.8K	JW 5.0MM	JW185	-	JW 5.0MM
R823	1.8K	3.3K	-	-	-
R834	220K	-	-	-	-