

# S102S01/S102S02 S202S01/S202S02

## SIP Type SSR for Medium Power Control

### ■ Features

1. High radiation resin mold package
2. RMS ON-state current  
 $I_T$  : 8 Arms at  $T_c \leq 80^\circ\text{C}$   
 (With heat sink)
3. Built-in zero-cross circuit  
 (S102S02/S202S02)
4. High repetitive peak OFF-state voltage  
 S102S01/S102S02  $V_{DRM}$ : MIN. 400V  
 S202S01/S202S02  $V_{DRM}$ : MIN. 600V
5. Isolation voltage between input and output  
 ( $V_{iso}$  : 4 000V<sub>rms</sub>)
6. Approved by CSA, No. LR63705  
 Recognized by UL, file No. E94758

### ■ Applications

1. Automatic vending machines, programmable controllers
2. Amusement equipment

### ■ Model Line-ups


	For 100V lines	For 200V lines
For phase control No built-in zero-cross circuit	<b>S102S01</b>	<b>S202S01</b>
Built-in zero-cross circuit	<b>S102S02</b>	<b>S202S02</b>

### ■ Absolute Maximum Ratings

Parameter	Symbol	Rating		Unit
		S102S01 S102S02	S202S01 S202S02	
Input	Forward current	50		mA
	Reverse voltage	6		V
Output	*1RMS ON-state current	8		A <sub>rms</sub>
	*2Peak one cycle surge current	80		A
	Repetitive peak OFF-state voltage	400	600	V
	Non-repetitive peak OFF-state voltage	400	600	V
	Critical rate of rise of ON-state current	50		A/ $\mu\text{s}$
Operating frequency	f	45 to 65		Hz
*3Isolation voltage	$V_{iso}$	4 000		V <sub>rms</sub>
Operating temperature	$T_{opr}$	- 25 to + 100		$^\circ\text{C}$
Storage temperature	$T_{stg}$	- 30 to + 125		$^\circ\text{C}$
*4Soldering temperature	$T_{sol}$	260		$^\circ\text{C}$

### ■ Outline Dimensions

(Unit : mm)



(Ta = 25°C)

\*1  $T_c \leq 80^\circ\text{C}$ \*2 50Hz sine wave,  $T_j = 25^\circ\text{C}$  start

\*3 60Hz AC for 1 minute, 40 to 60% RH, Apply voltages between input and output, by the dielectric withstand voltage tester with zero-cross circuit. (Input and output shall be shorted respectively).

(Note)

When the isolation voltage is necessary at using external heat sink, please use the insulation sheet.


\*4 For 10 seconds

## Electro-optical Characteristics

(Ta = 25°C)


Parameter		Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Input	Forward voltage	$V_F$	$I_F = 20\text{mA}$	-	1.2	1.4	V
	Reverse current	$I_R$	$V_R = 3\text{V}$	-	-	$10^{-4}$	A
Output	Repetitive peak OFF-state current	$I_{DRM}$	$V_D = V_{DRM}$	-	-	$10^{-4}$	A
	ON-state voltage	$V_T$	Resistance load $I_F = 20\text{mA}, I_T = 2\text{Arms}$	-	-	1.5	$V_{rms}$
	Holding current	$I_H$	-	-	-	50	mA
	Critical rate of rise of OFF-state voltage	$dV/dt$	$V_D = 2/3 \cdot V_{DRM}$	30	-	-	$V/\mu\text{s}$
	Critical rate of rise of commutating OFF-state voltage	$(dV/dt)_C$	$T_j = 125^\circ\text{C}, dI_T/dt = 4.0\text{A/ms}, V_D = 400\text{V}$	5	-	-	$V/\mu\text{s}$
	Zero-cross voltage	$V_{OX}$	$I_F = 8\text{mA}$	-	-	35	V
	Transfer characteristics	Minimum trigger current	$I_{FT}$	$V_D = 12\text{V}, R_L = 30\Omega$	-	-	8
$I_{FT}$			$V_D = 6\text{V}, R_L = 30\Omega$	-	-	8	mA
Isolation resistance		$R_{ISO}$	DC500V, 40 to 60 % RH	$10^{10}$	-	-	$\Omega$
Turn-on time		$t_{on}$	AC 50Hz	-	-	1	ms
		$t_{on}$	AC 50Hz	-	-	10	ms
Turn-off time		$t_{off}$	-	-	-	10	ms
Thermal resistance (Between junction and case)	$R_{th(j-c)}$	-	-	-	4.5	-	$^\circ\text{C/W}$
Thermal resistance (Between junction and ambience)	$R_{th(j-a)}$	-	-	-	40	-	$^\circ\text{C/W}$

**Fig. 1 RMS ON-state Current vs. Ambient Temperature**




- (1) With infinite heat sink
  - (2) With heat sink (200 x 200 x 2 mm Al plate)
  - (3) With heat sink (100 x 100 x 2 mm Al plate)
  - (4) With heat sink (75 x 75 x 2 mm Al plate)
  - (5) With heat sink (50 x 50 x 2 mm Al plate)
  - (6) Without heat sink
- (Note) With the Al heat sink set up vertically, tighten the device at the center of the Al heat sink with a torque of 0.4N • m and apply thermal conductive silicone grease on the heat sink mounting plate. Forcible cooling shall not be carried out.


**Fig. 2 RMS ON-state Current vs. Case Temperature**




**Fig. 3 Forward Current vs. Ambient Temperature**




**Fig. 4 Forward Current vs. Forward Voltage**




**Fig. 5 Surge Current vs. Power-on Cycle**




**Fig. 6 Maximum ON-state Power Dissipation vs. RMS ON-state Current (Typical Value)**



**Fig. 7 Minimum Trigger Current vs. Ambient Temperature (Typical Value)**



**Fig. 8 Repetitive Peak OFF-state Current vs. Ambient Temperature (Typical Value)**



● Please refer to the chapter “Precautions for Use”

### NOTICE

- The circuit application examples in this publication are provided to explain representative applications of SHARP devices and are not intended to guarantee any circuit design or license any intellectual property rights. SHARP takes no responsibility for any problems related to any intellectual property right of a third party resulting from the use of SHARP's devices.
- Contact SHARP in order to obtain the latest device specification sheets before using any SHARP device. SHARP reserves the right to make changes in the specifications, characteristics, data, materials, structure, and other contents described herein at any time without notice in order to improve design or reliability. Manufacturing locations are also subject to change without notice.
- Observe the following points when using any devices in this publication. SHARP takes no responsibility for damage caused by improper use of the devices which does not meet the conditions and absolute maximum ratings to be used specified in the relevant specification sheet nor meet the following conditions:
  - (i) The devices in this publication are designed for use in general electronic equipment designs such as:
    - Personal computers
    - Office automation equipment
    - Telecommunication equipment [terminal]
    - Test and measurement equipment
    - Industrial control
    - Audio visual equipment
    - Consumer electronics
  - (ii) Measures such as fail-safe function and redundant design should be taken to ensure reliability and safety when SHARP devices are used for or in connection with equipment that requires higher reliability such as:
    - Transportation control and safety equipment (i.e., aircraft, trains, automobiles, etc.)
    - Traffic signals
    - Gas leakage sensor breakers
    - Alarm equipment
    - Various safety devices, etc.
  - (iii) SHARP devices shall not be used for or in connection with equipment that requires an extremely high level of reliability and safety such as:
    - Space applications
    - Telecommunication equipment [trunk lines]
    - Nuclear power control equipment
    - Medical and other life support equipment (e.g., scuba).
- Contact a SHARP representative in advance when intending to use SHARP devices for any "specific" applications other than those recommended by SHARP or when it is unclear which category mentioned above controls the intended use.
- If the SHARP devices listed in this publication fall within the scope of strategic products described in the Foreign Exchange and Foreign Trade Control Law of Japan, it is necessary to obtain approval to export such SHARP devices.
- This publication is the proprietary product of SHARP and is copyrighted, with all rights reserved. Under the copyright laws, no part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, for any purpose, in whole or in part, without the express written permission of SHARP. Express written permission is also required before any use of this publication may be made by a third party.
- Contact and consult with a SHARP representative if there are any questions about the contents of this publication.