
MICROTHERM

Thermal Fuses JFM M



Construction:

Actual Opening Temperature The temperature at which fuse actually opens if measured in oil raised at 1K / min.

Rated Temperature (TF)


The temperature before which the fuse must open; as defined by Standards Bodies eg BEAB,UL,VDE.

Holding Temperature (TH)

Maximum temperature the fuse can withstand, carrying rated current, without opening for a period of time (IEC691), without causing premature ageing and nuisance tripping.

Maximum Temperature (TM)

The maximum temperature the fuse must not exceed once open to avoid breakdown of either its electrical or mechanical properties.



All dimensions in mm. NOT TO SCALE

Actual Rated Holding Approvals Max. CSA BEAB τυν Type Opening Opening Temp Temp UL VDE E142267 99254 18081- CAL0023R 9253021 Temp Temp (Tf) Th Tm 4510-8800AC1 98 ± 2℃ 75°C M10 102*°*C 165*°*C M20 110 ± 2℃ 115°C 85*°*C 165*°*C 120 ± 2 ℃ 90*°*C 165*°*C M30 125℃ M33 126 ± 2 ℃ 130°C 100*°*C 165 ℃

. . . .

Microtherm Ltd, Guildford, Surrey GU4 7WA

Tel +44 (0)1483 883969 • Fax +44 (0)1483 451816 • www.microtherm.co.uk • office@microtherm.co.uk

Features:

- Small physical size, ensures fast response to overtemperature.
- 1A 240Vac rated
- Thermal element protected mechanically and against oxidization.
- Single shot.Non resettable.
- Accurate melting points, range from 102°C to 130°C
- Long term stability

Applications Hints

Careful attention should be paid to following; Soldering must be carried out quickly and at the minimum of 10mm from the fuse body - pre tin-dipping is effective as is heat-sinking the leads.

Care must also be taken when bending the lead so as not to break the epoxy seal between the lead and case. The Holding Temperature of the fuse must not be exceeded under normal conditions. Failure to observe this may result in promoture tripping

this may result in premature tripping.

Order code JFM M _ _

