

DIFFERENT PART FOR SYSTEM

NO	LOC	NAME	P-B/G [TF]	P/S-B/G/D/K N-3/4 (AV) [TK]	P-I [TU]	P/S-B/G S-L/L [TA]
1	PWC1	POWER CORD	CW4232	KKP419C	CW3222	CW4232
2	U101	TUNER	3303KHC	3303KHC	DT2-1V17D	3303KHC
3	SF101	SAW FILTER	G1968M	K2950M	J1952M	G1968M
4	Z501	CERA FILTER	TP55.5MB	TP55.5MB	TP56.0MB	TP55.5MB
5	Z502	CERA FILTER	-	TP56.5MB	-	-
6	Z601	CERA FILTER	SF5H5.5MCB-	SF5H5.5MCB-	SFE6.0MB	SF5H5.5MCB-
7	Z602	CERA FILTER	-	SF5H6.5MCB-	-	-
8	I501	IC VCD	TDAB374A	TDAB374A	TDAB374A	DTAB374
9	I503	IC SECAM	-	TDAB395	-	TDAB395
10	C801	C LINE ACROSS	250V 0.47u	250V 0.1u	250V 0.47u	250V 0.47u
11	C802	C LINE ACROSS	250V 0.47u	250V 0.1u	250V 0.47u	250V 0.47u
12	XN01	X-TAL	-	3.58MHz	-	-
13	CN01	C CERA	-	50V 220	-	-
14	Q705	TR	KTC3198C	KTC3198C	-	KTC3198Y
15	Q706	TR	KTC3198C	KTC3198C	-	KTC3198Y
16	Q708	TR	KTA1266Y	KTA1266Y	-	KTA1266Y
17	Q709	TR	KTA1266Y	KTA1266Y	-	KTA1266Y
18	R728	R C-FILM	33K	33K	-	33K
19	R730	R C-FILM	33K	33K	-	33K
20	R732	R C-FILM	4.7K	4.7K	-	4.7K
21	R733	R C-FILM	4.7K	4.7K	-	4.7K
22	R736	R -CFILM	4.7K	4.7K	-	4.7K
23	R737	R C-FILM	4.7K	4.7K	-	4.7K
24	C104	C ELECTRO	50V 4.7u	50V 4.7u	50V 4.7u	50V 33u
25	C105	C ELECTRO	50V 4.7u	50V 4.7u	-	50V 4.7u
26	C106	C CERA	25V 0.01u	25V 0.01u	-	25V 0.01u
27	C107	C ELECTRO	50V 4.7u	50V 4.7u	-	50V 4.7u
28	C108	C CERA	25V 0.01u	25V 0.01u	-	25V 0.01u
29	Z101	CERA FILTER	-	-	-	MKT40WA100P
30	Z102	CERA FILTER	-	-	-	MKT40WA100P
31	IL01	IC AM DEMOD	-	-	-	STVB225
32	SL01	SAW FILTER	-	-	-	L9461M
33	QL01	TR	-	-	-	KTC 3198Y
34	QL02	TR	-	-	-	KTC 3198Y

DIFFERENT PARTS FOR SIZE

NO.	LOC.	14"			20"			21"	
		ORION	PHILIPS	POLKOLOR	ORION	SAMSUNG	POLKOLOR		ORION
1	CRT	A34JLL90X	A34EAC01X	A34EFU13X	A4BJLL90X	A48EQR11X	A48EEV33X	A51USW90X	A51EAL55X
2	SCT1	ISM003S	ISM003S	-	ISM003S	-	-	ISM003S	-
3	SCT2	-	-	ISHS09S	-	ISHS09S	ISHS09S	-	ISHS09S
4	D/COIL	DC-1450	DC-1450	DC-1450	DC-2050	DC-2050	DC-2050	DC-2070	DC-2070
5	RB01	EPCC180M290	EPCC180M290	EPCC180M290	EPCC180M290	EPCC180M290	EPCC180M290	EPCC140M290	EPCC140M290
6	LP04	-	MD-5	MD-5	-	-	MD-5	-	-
7	LP03	MD-5	-	-	MD-5	-	-	-	MD-5
8	L405	L-125	L-125	L-102	L-102	L-102	L-76	L-102	L-102
9	C409	2KV 470	2KV 470	2KV 470	2KV 470	2KV 1000	2KV 220	2KV 220	2KV 470
10	C410	1.6KV 7500	1.6KV 6200	1.6KV 6200	1.8KV 7500	1.8KV 8200	1.6KV 7200	1.8KV 6000	1.6KV 7500
11	C411	200V 0.51	200V 0.51	250V 0.6B	200V 0.47u	200V 0.51	200V 0.39u	200V 0.3u	200V 0.5
12	R302	1/6W 1.8K	1/6W 1.8K	1/6W 2.2K	1/6W 2.2K	1/6W 2.2K	1/6W 2.2K	1/6W 2.7K	1/6W 2.7K
13	R413	1/4W 120K	1/4W 120K	1/4W 68K	1/4W 68K	1/4W 68K	1/4W 82K	1/4W 88K	1/4W 82K
14	R415	1W 1.2(F) A	1W 0.47(F)	1W 0.18(F)	1W 2.4(F) A	1W 1(F)	1W 0.47(F)	1W 1.2(F) A	2W 2.7(F) A
15	RB07	1/4W 2.4K	1/4W 2.4K	1/4W 2.4K	1/4W 2.7K	1/4W 2.7K	1/4W 2.7K	1/4W 2.7K	1/4W 2.7K
16	R901-3	1/6W 3K	1/6W 3K	1/6W 3K	1/6W 2K	1/6W 2K	1/6W 2K	1/6W 2K	1/6W 2K
17	R904-6	1/6W 2K	1/6W 2K	1/6W 2K	1/6W 1.6K	1/6W 1.6K	1/6W 1.6K	1/6W 1.6K	1/6W 1.6K
18	P401	YFW500-05	YFW500-06	YFW500-06	YFW500-05	YFW500-08	YFW500-06	YFW500-06	YFW500-06
19	P401A	-	35135/0620+ 35179+ULW =350	35135/0620+ 35179+ULW =350	-	ODY-2190	ODY-2190	-	ODY-2190
20	ZZ132	140H-1015-IP	140H-1015-IP	140H-1015-IP	200H-1015-IF	200H-1015-IF	200H-1015-IP	210H-1015-IP	210H-1015-IP
21									
22									

DIFFERENT PART FOR SPEAKER (OPTION)

NO	ISPK	2SPK
1	SP01	3W 16 OHM
2	SP02	3W 8 OHM
3	R608	IK